

A Fast Algorithm for Computing the Fourier Spectrum of a Fractional Period

Jiasong Wang¹ and Changchuan Yin^{2,*}

¹ *Department of Mathematics, Nanjing University, Nanjing, Jiangsu 210093, China*

² *Department of Mathematics, Statistics and Computer Science, University of Illinois at Chicago, Chicago, IL 60607, USA*

Abstract. The Fourier spectrum at a fractional period is often examined when extracting features from biological sequences and time series. It reflects the inner information structure of the sequences. A fractional period is not uncommon in time series. A typical example is the 3.6 period in protein sequences, which determines the α -helix secondary structure. Computing the spectrum of a fractional period offers a high resolution insight into a time series. It has thus become an important approach in genomic analysis. However, computing Fourier spectra of fractional periods by the traditional Fourier transform is computationally expensive. In this paper, we present a novel, fast algorithm for computing the fractional period spectrum (FPS) of time series. The algorithm is based at the periodic distribution of signal strength at periodic positions of the time series. We provide theoretical analysis, deduction, and special techniques for reducing computational costs of the algorithm. The analysis of computational complexity of the algorithm shows that the algorithm is much faster than traditional Fourier transform. Our algorithm can be applied to effectively computing fractional periods in time series from a broad of research fields.

AMS subject classifications: 42A38, 92D20

Key words: Fourier transform, periodicity, fractional period spectrum

1. Introduction

Signal processing approaches have been widely applied in the periodicity analysis of time series, and thus becoming a major research tool for bioinformatics [1, 3]. The main requisite in applying signal processing to symbolic sequences is mapping the sequences onto numerical time series. For example, we previously presented a numerical representation of DNA sequences without degeneracy [17]. After numerical mapping, mathematical methods can be employed to study features, structures, and functions of the symbolic sequences. The most common signal processing approach is Fourier transform [16], which has been widely used to study periodicity and repetitive regions in symbolic DNA

*Corresponding author. *Email addresses:* cyin1@uic.edu

sequences [1, 10], as well as in genome comparison [19, 23]. We have studied the mathematical properties of the Fourier spectrum for symbolic sequences [13, 14]. For a review of mathematical methods for the study of biological sequences, one may refer to our book [15].

Periods in biological sequences can be categorized into two types: integer periods and fractional periods. For integer periods, the 3-base periodicity of protein coding regions is often used in gene finding [11, 18, 21, 22]; 2-base periodicity was found in introns of genomes [2]. 2-period exists in protein sequence regions for beta sheet structures. As indicated by their name, fractional periods do not correspond to an integer number of cycles in numerical series. Fractional periods are prevalent and important in structures and functions of protein sequences and genomes. For example, the 3.6-period in protein sequences determines the α -helix secondary structure [4, 5, 7]. Strong 10.4- or 10.5-base periodicity in genomes are associated with nucleosomes [9, 12]. The 6.5-base periodicity is present in *C. elegans* introns [8]. Fractional period spectrum may offer high resolution and precise features of sequences. However, the fast Fourier transform (FFT) can not be used for computing spectra of fractional periods, identifying fractional period features in a large genome is challenging. The demand of the periodicity research of DNA and protein sequences motivates us to investigate advanced techniques for fractional periodicity analysis of time series, which correspond to biological symbolic sequences.

With the quickly growing volume of genomics sequences of human and model organisms, there is a strong demand to characterize not only integer periods but also fractional periods in genomic and protein sequences. We previously proposed a periodic power spectrum (PPS) method based at periodic distributions of signal strength on periodic positions [14, 20]. The main advantage the PPS method is that it can avoid spectral leakage and reduce background noise, which both appear in power spectrum in Fourier transform. Thus, the PPS method can capture all latent integer periodicities in DNA sequences. We have applied this method in detection of latent periodicities in different genome elements, including exons and microsatellite DNA sequences.

This paper extends the PPS method to suggest a novel method for fast calculating Fourier spectrum of fractional period. This method will be also helpful in computing the fractional period spectrum for any time series from science and technology fields outside of bioinformatics.

2. Methods Deduced

2.1. Fourier transform and congruence derivative sequence

For a numerical sequence x of length m , consisting of $x_0, x_1, \dots, x_{m-1}$, its discrete Fourier transform (DFT) at frequency k is defined as [16]

$$X(k) = \sum_{j=0}^{m-1} x_j e^{-i2\pi kj/m}, i = \sqrt{-1}, k = 0, 1, \dots, m-1 \quad (2.1)$$

And its Fourier power spectrum at frequency k is defined as [16]

$$\begin{aligned}
 PS(k) &= X^*(k)X(k) \\
 &= \left(\sum_{j=0}^{m-1} x_j e^{-i2\pi jk/m} \right)^* \left(\sum_{j=0}^{m-1} x_j e^{-i2\pi jk/m} \right) \\
 i &= \sqrt{-1}, k = 0, 1, \dots, m-1
 \end{aligned} \tag{2.2}$$

where $*$ indicates the complex conjugate. Because our method is applied to researching the periodicity of sequence by using Fourier spectrum, for convenience, the frequency k/m is called period m/k . In this paper, we directly define the DFT spectrum by period instead of frequency.

We want to compute Fourier spectrum at period l/k , $l > k$ and l, k are smaller than m . Using traditional formula of Fourier transform, we need to calculate Fourier transform

$$X(k) = \sum_{j=0}^{m-1} x_j e^{\frac{-i2\pi jk}{l}} \tag{2.3}$$

Then, its spectrum at period l/k or at frequency k is

$$PS(k) = \left(\sum_{j=0}^{m-1} x_j e^{\frac{-i2\pi jk}{l}} \right)^* \left(\sum_{j=0}^{m-1} x_j e^{\frac{-i2\pi jk}{l}} \right) \tag{2.4}$$

We will introduce a fast method for computing the Fourier spectrum at period l/k . We previously demonstrate that the Fourier power spectrum of a numerical sequence is determined by the distribution of signal strength at periodic positions in this sequence [14, 20]. The distribution can be represented and measured by a congruence derivative vector of the sequence, which is defined as follows.

Definition 2.1. For a numerical sequence x of length m , if two positive integers n and l satisfy $m = nl$, then the congruence derivative sequence of x has a length of l and is defined as follows

$$y_t = \sum_{j=0}^{n-1} x_{jl+t}, t = 0, 1, \dots, l-1 \tag{2.5}$$

The following deduced theorems indicate that the congruence derivative sequence of length l of the numerical sequence x can be used to compute periodic power spectrum at period l . The Fourier transform of the congruence derivative sequence y is

$$Y(k) = \sum_{t=0}^{l-1} y_t e^{-i2\pi tk/l}, k = 0, 1, \dots, l-1 \tag{2.6}$$

The relationship between Fourier transform of the original sequence and its congruence derivative sequence was introduced in [14, 20]. The DFT of sequence x at frequency

$n = m/l$ is the same as the DFT of the congruence derivative sequence y at frequency 1.

$$X(n) = X(m/l) = Y(1) \quad (2.7)$$

This formula is the mathematical ground of the PPS method. The following theorem extends the conclusion to a general case.

Theorem 2.1. *For a numerical sequence x of length m , suppose $n = m/l$, then the DFT of the numerical sequence x at frequency kn is*

$$X(kn) = Y(k), 0 \leq k \leq l-1 \quad (2.8)$$

Proof. We know

$$\begin{aligned} Y(k) &= \sum_{t=0}^{l-1} y_t e^{-i2\pi tk/l} = \sum_{t=0}^{l-1} \sum_{j=0}^{n-1} x_{jl+t} e^{-i2\pi tk/l} = \sum_{t=0}^{l-1} \sum_{j=0}^{n-1} x_{jl+t} e^{-i2\pi(jl+t)k/l} = \sum_{r=0}^{m-1} x_r e^{-i2\pi rk/m} \\ &= X(kn) \end{aligned}$$

The proof of Theorem 2.1 indicates that the property of conjugate symmetry in DFT of a real sequence is preserved. We thus have the following corollary.

Corollary 2.1.

$$X(kn) = X^*((l-k)n), 1 \leq k \leq l-1 \quad (2.9)$$

According to formula 2.2, Fourier power spectrum of sequence x at frequency kn is defined as

$$PS(kn) = X^*(kn)X(kn) = X^*(km/l)X(km/l) = Y^*(k)Y(k). \quad (2.10)$$

Definition 2.2. *If $m = nl$, the DFT spectrum of numerical sequence x at fractional period l/k is named the fractional period spectrum (FPS) and is written as $FPS(l/k) = Y^*(k)Y(k), 1 \leq k \leq l-1$*

Definition 2.3. *For a numerical sequence of length l , $y_t, t = 0, 1, \dots, l-1$, its self q -shift summation is defined by*

$$z_{l,q} = \sum_{t=0}^{l-1} y_t y_{t+q} \quad (2.11)$$

with $t+q$ taken modulo l , $0 \leq q < l$.

If we write sequence $y_t, t = 0, 1, \dots, l-1$, as a vector, $y^T = [y_0, y_1, \dots, y_{l-1}]$, then $z_{l,q}$ can be realized by the autocorrelation of vector y . For a special case, $z_{l,0}$ is equal to the inner product of vector y , or $z_{l,0} = y^T y$.

From the definition of DFT of the congruence derivative sequence (formula 2.6), we have

$$Y(k) = \sum_{t=0}^{l-1} y_t e^{-i2\pi tk/l} = \sum_{t=0}^{l-1} y_t \cos(2\pi tk/l) - i \sum_{t=0}^{l-1} y_t \sin(2\pi tk/l) \quad (2.12)$$

From the definition of FPS , $FPS(l/k) = Y^*(k)Y(k)$, we notice that

$$FPS(l/k) = \left(\sum_{t=0}^{l-1} y_t \cos(2\pi tk/l) \right)^2 + \left(\sum_{t=0}^{l-1} y_t \sin(2\pi tk/l) \right)^2 \quad (2.13)$$

which is real quadratic form of l variables, $y_0, y_1, \dots, y_{l-1}$, can be written as

$$FPS(l/k) = y^t A y \quad (2.14)$$

where the coefficient matrix $A = a_{rs}$ is of quadratic form, in which

$$a_{rs} = \cos(r-l)\frac{2k\pi}{l} \cos(s-l)\frac{2k\pi}{l} + \sin(r-l)\frac{2k\pi}{l} \sin(s-l)\frac{2k\pi}{l} \quad (2.15)$$

$$r, s = 1, 2, \dots, l$$

After reorganizing formula 2.15, we obtain the following theorem about the coefficient matrix A .

Theorem 2.2. *The coefficient matrix of the quadratic form, A , is a symmetric matrix.*

Proof. According to some fundamental identities of trigonometry,

$$a_{rs} = \cos(r-l)\frac{2k\pi}{l} \cos(s-l)\frac{2k\pi}{l} + \sin(r-l)\frac{2k\pi}{l} \sin(s-l)\frac{2k\pi}{l}$$

would be equal to $\cos(r-l-(s-l))\frac{2k\pi}{l} = \cos(r-s)\frac{2k\pi}{l}$, i.e., $a_{rs} = \cos(r-s)\frac{2k\pi}{l}$.

It is clear that $a_{rs} = a_{sr}$, so the coefficient matrix A is symmetric.

Theorem 2.3. *For a numerical sequence x of length m , if $m = nl$ and its congruence derivative sequence is $y_t, t = 0, 1, \dots, l-1$, then $FPS(l/k)$ of the sequence x can be expressed as follows.*

If l is an odd number,

$$FPS(l/k) = z_{l,0} + 2 \sum_{q=1}^{\frac{l-1}{2}} z_{l,q} \cos(q) \frac{2k\pi}{l}.$$

If l is an even number,

$$FPS(l/k) = z_{l,0} + \sum_{q=1}^{\frac{l}{2}-1} z_{l,q} \cos(q) \frac{2k\pi}{l} + 2 \cos\left(\frac{l}{2}\right) \frac{2k\pi}{l} \sum_{t=0}^{\frac{l}{2}-1} y_t y_{t+\frac{l}{2}}.$$

Proof.

It is clear the diagonal elements of the coefficient matrix A are unit elements. Due to the symmetry of matrix A , we only need to check the lower triangular matrix of A under the diagonal of A , which is sufficient for proof.

The element of the lower triangular matrix of A , $a_{rs} = \cos(r-s)\frac{2k\pi}{l}$, $r = 2, 3, \dots, l$, $r > s$, also has some kind of symmetry. The result is as follows.

When l is an odd number, $a_{21} = a_{32} = a_{43} = \dots = a_{l(l-1)} = \cos(1)\frac{2k\pi}{l}$ and $a_{21}, a_{32}, \dots, a_{l(l-1)}$ also are equal to a_{l1} because $\cos(l-t)\frac{2k\pi}{l} = \cos(t)\frac{2k\pi}{l}$ for $t = 1, 2, \dots, l$. Similarly, $a_{31} = a_{42} = \dots = a_{l(l-2)} = a_{l(l-1)} = a_{l2} = \cos(2)\frac{2k\pi}{l}, \dots$. Noticed $\cos(l-t) = \cos(t)$ for $t = 1, \dots, l$, then $a_{31} = a_{42} = \dots = a_{l(l-2)} = a_{l(l-1)} = a_{l2} = \cos(2)\frac{2k\pi}{l}, \dots, a_{(l+1)/21} = a_{(l+3)/22} = \dots, a_{l(l+1)/2} = a_{(l+3)/21} = \dots, a_{l(l-1)/2} = \cos((l-1)/2)\frac{2k\pi}{l}$.

When l is an even number, we have $a_{21} = a_{32} = a_{43} = \dots = a_{l(l-1)} = a_{l(l-1)} = a_{l1} = \cos(1)\frac{2k\pi}{l}$ and $a_{31} = a_{42} = \dots = a_{l(l-2)} = a_{l(l-1)} = a_{l(l-1)1} = a_{l2} = \cos(2)\frac{2k\pi}{l}$. In general, $a_{l/21} = a_{(l/2+1)/2} = \dots, a_{l(l/2+1)} = a_{(l/2+2)1} = a_{(l/2+3)/2} = \dots, a_{l(l/2-1)} = \cos(l/2-1)\frac{2k\pi}{l}$, and $a_{(l/2+1)/1} = a_{(l/2+2)2} = \dots, a_{ll/2} = \cos(l/2)\frac{2k\pi}{l}$.

We then substitute those results into the coefficient matrix of the quadratic form A for the $FPS(l/k)$. The following formulas can be obtained.

If l is an odd number,

$$\begin{aligned}
 FPS(l/k) = & y_0^2 + y_1^2 + y_2^2 + \dots + y_{l-1}^2 \\
 & + 2\cos(1)\frac{2k\pi}{l}(y_0y_1 + y_1y_2 + y_2y_3 + y_3y_4 \dots y_0y_{l-1}) \\
 & + 2\cos(2)\frac{2k\pi}{l}(y_0y_2 + y_1y_3 + y_2y_4 + y_3y_5 \dots y_{l-2}y_0 + y_{l-1}y_1) \\
 & + 2\cos(3)\frac{2k\pi}{l}(y_0y_3 + y_1y_4 + y_2y_5 + y_3y_6 \dots y_{l-3}y_0 + y_{l-2}y_1 + y_{l-1}y_2) \\
 & \dots \\
 & + 2\cos((l-1)/2)\frac{2k\pi}{l}(y_0y_{(l-1)/2} + y_1y_{(l+1)/2} + y_2y_{(l+3)/2} + \\
 & \dots y_{(l-(l-1)/2)}y_0 + \dots + y_{l-1}y_{(l-3)/2}).
 \end{aligned} \tag{2.16}$$

If l is an even number,

$$\begin{aligned}
 FPS(l/k) = & y_0^2 + y_1^2 + y_2^2 + \dots + y_{l-1}^2 \\
 & + 2\cos(1)\frac{2k\pi}{l}(y_0y_1 + y_1y_2 + y_2y_3 + y_3y_4 \dots y_0y_{l-1}) \\
 & + 2\cos(2)\frac{2k\pi}{l}(y_0y_2 + y_1y_3 + y_2y_4 + y_3y_5 \dots y_{l-2}y_0 + y_{l-1}y_1) \\
 & + 2\cos(3)\frac{2k\pi}{l}(y_0y_3 + y_1y_4 + y_2y_5 + y_3y_6 \dots y_{l-3}y_0 + y_{l-2}y_1 + y_{l-1}y_2) \\
 & \dots \\
 & + 2\cos(l/2-1)\frac{2k\pi}{l}(y_0y_{l/2-1} + y_1y_{l/2} + y_2y_{l/2+1} + \dots y_{l-3}y_{l/2-2} + y_{l-2}y_{l/2-1} + y_{l-1}y_{l/2}) \\
 & + 2\cos(l/2)\frac{2k\pi}{l}(y_0y_{l/2} + y_1y_{l/2+1} + y_2y_{l/2+2} + \dots y_{l/2-1}y_{l-1}).
 \end{aligned} \tag{2.17}$$

The last term in equation (2.16), $\cos(l/2)\frac{2k\pi}{l}(y_0y_{l/2} + y_1y_{l/2+1} + y_2y_{l/2+2} + \cdots + y_{l/2-1}y_{l-1})$ can be written as $\cos(l/2)\frac{2k\pi}{l} \sum_{t=0}^{l/2-1} y_t y_{t+l/2}$. Noticing the definition of $z_{l,q}$, the formulas (2.15) and (2.16) may be written as follows.

If l is an odd number,

$$FPS(l/k) = z_{l,0} + 2 \sum_{q=1}^{\frac{l-1}{2}} z_{l,q} \cos(q) \frac{2k\pi}{l}. \quad (2.18)$$

If l is an even number,

$$FPS(l/k) = z_{l,0} + 2 \sum_{q=1}^{\frac{l}{2}-1} z_{l,q} \cos(q) \frac{2k\pi}{l} + 2 \cos\left(\frac{l}{2}\right) \frac{2k\pi}{l} \sum_{t=0}^{\frac{l}{2}-1} y_t y_{t+\frac{l}{2}}. \quad (2.19)$$

Based on Theorem 2.3 and Corollary 2.1, $FPS(l/k)$ may be re-written by following theorem, which may improve the technique for computing $FPS(l/k)$.

Theorem 2.4.

$$FPS(l/k) = FPS(l/l - k), 1 \leq k \leq l - 1. \quad (2.20)$$

According to Theorem 2.4, to compute all of the $FPS(l/k)$, $1 \leq k \leq l - 1$, we only require about half of computing costs.

For $k = 1$, noticing formulas 2.18 and 2.19 and the symmetry of $FPS(l/k)$, we only need to calculate $(l - 1)/2$ coefficients of quadratics $y_0, y_1, \dots, y_{l-1}$ when l is an odd number; and $l/2$ coefficients when l is an even number.

It is valuable to notice on the property of a cosine function,

$$\cos(q) \frac{2k\pi}{l} = \cos(q) \frac{2(l-k)\pi}{l}, 0 \leq k \leq l - 1. \quad (2.21)$$

Certainly, it is the foundation of Theorem 2.4 and an important formula to prove the following theorem.

Theorem 2.5. *The coefficient matrix of quadratic form A when $k = 1$ is sufficient for computing $FPS(l/k)$ when $k \neq 1$.*

Proof.

Without loss of generality, we show the case when l is an odd number. For a fixed k , $k \neq 1$, from Theorem 2.4, the range of k should be in $2 \leq k \leq (l - 1)/2$ and the $(l - 1)/2$ coefficients of quadratics of $y_0, y_1, \dots, y_{l-1}$ are $\cos(t) \frac{2k\pi}{l}$, $t = 1, 2, \dots, \frac{l-1}{2}$.

For $k = 1$, we obtain the coefficients $\cos(q) \frac{2\pi}{l}$, $q = 1, 2, \dots, \frac{l-1}{2}$.

If the $(l - 1)/2$ coefficients, $\cos(t) \frac{2k\pi}{l}$, $t = 1, 2, \dots, (l - 1)/2$ can be represented by $\cos(q) \frac{2\pi}{l}$, $q = 1, 2, \dots, (l - 1)/2$, then, the proposition is proved.

It is known that the interval of k is $[2, (l-1)/2]$, so, for $t = 1 \cos(k) \frac{2\pi}{l}$, the first coefficient of $FPS(l/k)$, is one of $\cos(q) \frac{2\pi}{l}$, $q = 1, 2, \dots, (l-1)/2$. When $t \neq 1$, we must have two results: if $t \times k$ in the interval $[1, (l-1)/2]$, it is easy to see $\cos(t) \frac{2k\pi}{l}$ is one of $\cos(q) \frac{2\pi}{l}$, $q = 1, 2, \dots, (l-1)/2$; otherwise, if $q \times k > (l-1)/2$, rely on formula (2.19) since $l - q \times k$ belongs to $[1, (l-1)/2]$.

3. Fast Algorithm

3.1. Fast algorithm for computing fractional period spectrum at period l/k

Based on Theorem 2.5, the algorithm should do a build-in data in the computer. The data contains the coefficients of quadratics, when $k = 1$ and for periods, $l = 2, 3, \dots$, to store in the computer. The build-in data save much computing time because the algorithm does not need to repeatedly find the coefficients for next user.

The programs shall design two functions. One function is to obtain the congruence derivative sequence shall be designed and named CDS (Y). CDS is (Congruence Derivative Sequence). The other function $Z(l, t)$ is to yield the autocorrelation of the congruence derivative sequence with two parameters l and q .

A MATLAB function $rem(p, l)$ may be used for p and l are integer number if the programming is written by MATLAB, where the $rem(p, l)$ means the remainder after p divided by l .

Given input original sequence x , the function CDS (Y) yields the congruence derivative sequence of the sequence x for a period l in the computation.

Suppose we need calculate the fractional period l/k , we then have the following algorithm.

If l is odd number, complete the loop for ordering to take out $(l-1)/2$ coefficients of quadratics, $\cos(1) \frac{2\pi}{l}$, $\cos(2) \frac{2\pi}{l}$, $\dots$, $\cos((l-1)/2) \frac{2\pi}{l}$, from the build-in data. From $t = 1$ to $(l-1)/2$, do if $r = rem(t * k, l) > (l-1)/2$ then take $\cos(l-r) \frac{2\pi}{l}$ else take $\cos(r) \frac{2\pi}{l}$. At the same time, the $2 \cos() \frac{2\pi}{l}$ value times the $Z(l, t)$ and to do summation corresponding to t order until $t = (l-1)/2$. The computed summation added with $Z(l, 0)$ is the $FPS(l/k)$.

If l is even number, doing the loop for ordering to take out $l/2$ coefficients of quadratics, $\cos(1) \frac{2\pi}{l}$, $\cos(2) \frac{2\pi}{l}$, $\dots$, $\cos(l/2) \frac{2\pi}{l}$, from the build-in data, i.e., $t = 1$ to $(l-1)/2$ do if $r = rem(t * k, l) > (l)/2$ then take $\cos(l-r) \frac{2\pi}{l}$ else take $\cos(r) \frac{2\pi}{l}$. At the same time, the $2 \cos() \frac{2\pi}{l}$ value times the $Z(l, t)$ to do summation corresponding to t order until $t = (l/2 - 1)$. $FPS(l/k)$ will be the computed summation added with two quantities, $2 \cos(l/2) \frac{2k\pi}{l}$ timing $\sum_{t=0}^{l/2-1} y_t y_{t+l/2}$, and $Z(l, 0)$.

3.2. Computational complexity of the FPS algorithm

The FPS algorithm computes the spectrum of a certain fractional period $FPS(l/k)$. If $FPS(l/k)$ for $k = 1$ is obtained, the algorithm can easily calculate $FPS(l/k)$ at some k , $2 \leq k \leq l - 1$. Computing $FPS(l/1)$ from the congruence derivative sequence, y , which is yielded from the original sequence of length m , has a computational complexity $O(n)$ if l is relatively small compared with m . The second step in the algorithm is to compute $z_{l,q}$ when l is an even or odd number, the algorithm needs approximate $l/2(l+1)$ multiplications. Finally, using formulas (2.18,2.19) needs $l/2$ multiplications to determine the value of $z_{l,q} * \cos(q)2k\pi/l$. So the total computational quantity for the FPS algorithm involves $l/2(l+1) + l/2 = l^2/2 + l$ multiplications, i.e., the computational complexity is then $O(l^2 + l)$.

It shall be noted that fast Fourier transform (FFT) was designed to compute Fourier transform for frequency, and is not applicable to computing Fourier spectra for fractional periods. Using the traditional Fourier transform to compute $FPS(l/k)$, we need to calculate the Fourier transform at period l/k by the formulas 2.3 and 2.4.

From (2.3), we must calculate m exponents, $-i2\pi jk/l, j = 0, 1, 2, \dots, m-1$, and call exp function m times to figure out $e^{-i2\pi jk/l}, j = 0, 1, 2, \dots, m-1$, if using MATLAB. It is known that to compute function $e^{-i2\pi jk/l}$ costs much time. Then to figure out $\sum_{j=0}^{m-1} e^{-i2\pi jk/l}$ total needs $2m$ multiplications and the time for calling m exp functions. So, according to formula (2.4) calculating out the Fourier spectrum at period l/k needs $2m+1$ multiplications, i.e., $O(m)$ computational costs.

Further comparison of computational costs between the two methods shows that if m is a medium size, our algorithm may not have a large advantage. However, for biological sequences such as genomes, the length of numerical sequence m is very large, and l is much smaller than m , then, $O(l^2 + l)$ is very small and can be ignored. The computation complexity of the proposed FPS algorithm is linear $O(n)$, ($n < m$). We should notice that the computation of exponential function costs a great amount of time in traditional Fourier transform for calculating FPS. If $FPS(l/k)$ is computed for more fractional periods $2 \leq k \leq l-1$, traditional Fourier transform needs $tO(m)$ costs where t is the number of fractional periods to be computed. In summary, the analysis of computational complexity indicates that the FPS algorithm is much faster than traditional Fourier transform for computing fractional spectrum.

4. Conclusions

A fast algorithm for computing the FPS of biological sequences is introduced in this paper. First, the mathematical deduction and proof are presented. Then, based on the mathematical theory, the technique of build-in data is suggested and some functions are introduced, so that a simple program can be designed. The analysis of computational complicity shows that this fast algorithm is much faster than traditional Fourier transform.

The fast algorithm will be also helpful in computing the FPS for any time series from the science and technology field other than bioinformatics.

In addition, the congruence derivative sequence of original sequences can be used to yield Ramanujan transform easily [6, 24], which do not have any computing cost. The computation for identifying periods of the biological sequence or other time series would be done by Fourier transform and Ramanujan transform simultaneously.

References

- [1] ANASTASSIOU, D. Genomic signal processing. *Signal Processing Magazine, IEEE* 18, 4 (2001), 8–20.
- [2] ARQUÈS, D. G., AND MICHEL, C. J. Periodicities in introns. *Nucleic acids research* 15, 18 (1987), 7581–7592.
- [3] CHEN, J., LI, H., SUN, K., AND KIM, B. How will bioinformatics impact signal processing research? *Signal Processing Magazine, IEEE* 20, 6 (2003), 106–206.
- [4] EISENBERG, D., WEISS, R., AND TERWILLIGER, T. The hydrophobic moment detects periodicity in protein hydrophobicity. *Proc. Natl. Acad. Sci.* 81 (1984), 140–144.
- [5] GRUBER, M., SÖDING, J., AND LUPAS, A. N. Repetitions and their periodicities in fibrous proteins. *Nucleic Acids Research* 33, suppl 2 (2005), W239–W243.
- [6] HUA, W., WANG, J., AND ZHAO, J. Discrete ramanujan transform for distinguishing the protein coding regions from other regions. *Molecular and cellular probes* 28, 5 (2014), 228–236.
- [7] LEONOV, H., AND ARKIN, I. T. A periodicity analysis of transmembrane helices. *Bioinformatics* 21, 11 (2005), 2604–2610.
- [8] MESSAOUDI, I., OUESLATI, A. E., AND LACHIRI, Z. Detection of the 6.5-base periodicity in the c. elegans introns based on the frequency chaos game signal and the complex morlet wavelet analysis. *International Journal of Scientific Engineering and Technology* 2, 12 (2013), 1247–1251.
- [9] SALIH, B., AND TRIFONOV, E. N. Strong nucleosomes reside in meiotic centromeres of c. elegans. *Journal of Biomolecular Structure and Dynamics* 33, 2 (2015), 365–373.
- [10] SILVERMAN, B., AND LINSKER, R. A measure of DNA periodicity. *Journal of theoretical biology* 118, 3 (1986), 295–300.
- [11] TIWARI, S., RAMACHANDRAN, S., BHATTACHARYA, A., BHATTACHARYA, S., AND RAMASWAMY, R. Prediction of probable genes by fourier analysis of genomic sequences. *Bioinformatics* 13, 3 (1997), 263–270.
- [12] TRIFONOV, E. N. 3-, 10.5-, 200- and 400-base periodicities in genome sequences. *Physica A: Statistical Mechanics and its Applications* 249, 1 (1998), 511–516.
- [13] WANG, J., DANG, C., AND YIN, C. A comparative study of the signal-to-noise ratios of different representations for symbolic sequences. *Journal of Applied Mathematics and Bioinformatics* 372 (2014), 135–145.
- [14] WANG, J., LIU, G., AND ZHAO, J. Some features of Fourier spectrum for symbolic sequences. *Numerical Mathematics A Journal of Chinese Universities*, 4 (2012), 341–356.
- [15] WANG, J., AND YAN, M. *Numerical Methods in Bioinformatics: An Introduction*. Science Press, 2013.
- [16] WELCH, P. D. The use of fast Fourier transform for the estimation of power spectra: A method based on time averaging over short, modified periodograms. *IEEE Transactions on audio and electroacoustics* 15, 2 (1967), 70–73.
- [17] YAU, S. S.-T., WANG, J., NIKNEJAD, A., LU, C., JIN, N., AND HO, Y.-K. DNA sequence representation without degeneracy. *Nucleic Acids Research* 31, 12 (2003), 3078–3080.
- [18] YIN, C. Representation of DNA sequences in genetic codon context with applications in exon and intron prediction. *Journal of Bioinformatics and Computational Biology* 13, 2 (2015), 1550004–2.
- [19] YIN, C., CHEN, Y., AND YAU, S. S.-T. A measure of DNA sequence similarity by fourier transform with applications on hierarchical clustering. *Journal of Theoretical Biology* 359 (2014), 18–28.
- [20] YIN, C., AND WANG, J. Periodic power spectrum with applications in detection of latent peri-

- odicities in DNA sequences. *Journal of Mathematical Biology* 00 (2016), 00–00.
- [21] YIN, C., AND YAU, S. S.-T. A Fourier characteristic of coding sequences: origins and a non-Fourier approximation. *Journal of Computational Biology* 12, 9 (2005), 1153–1165.
 - [22] YIN, C., AND YAU, S. S.-T. Prediction of protein coding regions by the 3-base periodicity analysis of a DNA sequence. *Journal of Theoretical Biology* 247, 4 (2007), 687–694.
 - [23] YIN, C., AND YAU, S. S.-T. An improved model for whole genome phylogenetic analysis by Fourier transform. *Journal of Theoretical Biology* 359, 21 (2015), 18–28.
 - [24] YIN, C., YIN, X. E., AND WANG, J. A novel method for comparative analysis of DNA sequences by Ramanujan-Fourier transform. *Journal of Computational Biology* 21, 12 (2014), 867–879.